

IMPORTANT

Read This First

The following instructions apply only if your software was not factory installed or if you need to re-install the software at a future time. The actual kit is provided for backup purposes.

Before you install MS-DOS Version 5.0 onto your DECpc, you must read the file named README.1ST on Disk 1.

Follow these steps to read the file:

1. Insert the diskette labeled Digital MS-DOS Ver 5.0 Disk 1 into Drive A.
2. Start the system.
3. Press the F3 key when the screen displays "Welcome to Setup."
The "EXITING SETUP" screen then displays.
4. Press Y to display the MS-DOS prompt.
5. Type the following then press <ENTER> to read the file:

```
TYPE README.1ST
```

To start and stop the text scrolling on the screen, simultaneously press the CTRL and S keys.

Copyright Digital Equipment Corporation 1992
MS-DOS and Windows are registered trademark of Microsoft Corporation.

AV-PA41E-TK

Enhancements to Digital's Windows 3.1

The printer drivers found on the DOS 5.0 Supplemental Drivers diskette are Windows 3.0 print drivers. Windows 3.1 printer drivers are included in the Windows 3.1 kit.

The Windows 3.1 kit installation procedure has been expanded to include drivers for the following additional DEC printers:

- Digital DEClaser 1100
- Digital DEClaser 2100/plus
- Digital DEClaser 2200/plus
- Digital DEClaser 3200
- Digital LN03/PLUS
- Digital LA70
- Digital LA75
- Digital LA75 Plus
- Digital LA324
- Digital LA424
- Digital LJ250/LJ252
- Digital DECmultiJET 1000
- Digital DECmultiJET 2000
- Digital LN03 Printer

The RGDI video drivers necessary for the DECpc 433W and the IGC video board are included in this kit.

DECpc 433W and IGC Board Installation Procedure

When installing Windows 3.1 on a DECpc 433W or other DECpc system with an optional IGC video board use the following installation procedure:

1. Install new video utilities by inserting the Windows 3.1 Supplemental Drivers disk into drive A and type A: <ENTER> at the DOS prompt.
2. Type INSTALL <ENTER> to install the video drivers. Note the install program will create a CONFIG.NEW and an AUTOEXEC.NEW in the root directory.

3. If you wish to retain your old CONFIG.SYS and AUTOEXEC.BAT files, rename them and copy CONFIG.NEW to CONFIG.SYS and copy AUTOEXEC.NEW to AUTOEXEC.BAT.

To use the TIGA video drivers:

4. Edit AUTOEXEC.BAT and add the following line below the "SET TIGA = " command line:

```
C:\DRIVERS\VIDEONTIGACD
```

5. Reboot the system.
6. Run Windows 3.1 setup. When setup displays its configuration, select "TIGA (large font)" or "TIGA (small fonts)". Follow the Windows setup instructions to install the appropriate driver.
7. Restart Windows.

Or to use the RGDI video drivers:

4. Reboot your system.
5. Run Windows 3.1 setup. When setup display its configuration, select either "RGDI Windows large fonts" or "RGDI Windows small fonts" and follow the instructions to install the appropriate drivers.
6. Restart Windows